



Dimensions in Inches

Part Numbers	Adapter Code	$\varnothing A$	$\varnothing B$	$\varnothing C$	$\varnothing D$	H	ISO / ISO	Fits Actuator Series
2021-401	A	.713	.551	.866	.670	.827	F05 / F07	2021-2031 2121-2131
2021-402	B	.874	.670	1.102	.866	1.063	F07 / F10	2036-2046 2136-2146
2021-403	C	1.110	.866	1.417	1.063	1.339	F10 / F12	2051-2056 2151-2156
2021-404	D	1.417	1.063	1.889	1.417	1.812	F12 / F14	2061-2066 2161-2166
2021-405	E	--	.551	--	.866	1.063	F05 / F10	2036-2046 2136-2146
2021-406	F	--	.670	--	1.063	1.339	F07 / F12	2051-2056 2151-2156

Note: 1. Adapters 2021 - 405 and 2021-406 requires 2 individual adapters to make a complete adapter
 2. Adapter 2021 - 405 requires adapters 2021 - 401 and 2021 - 401 and 2021 - 402 to form a complete adapter.
 3. Adapter 2021 - 406 requires adapters 2021 - 402 and 2021 - 402 and 2021 - 403 to form a complete adapter.